



Specifications Philips HF-P 118/136 TL-D III 220-240V 50/60 Hz for 1x18W & 1x36W  
[View Product](#)

General

Full box quantity 12

General Information

|                          |                                         |
|--------------------------|-----------------------------------------|
| SKU                      | 137168                                  |
| EAN                      | 8711500999641                           |
| Brand                    | Philips                                 |
| Manufacturer Name        | HF-P 118/136 TL-D III 220-240V 50/60 Hz |
| Energy efficiency class  | A                                       |
| Any Lamp all-in warranty | 1 Year                                  |

Technical Information

|                          |                                 |
|--------------------------|---------------------------------|
| Technology               | Accessory                       |
| Wattage                  | 0                               |
| Ballast                  | Electronic (HF) without starter |
| Ballast for bulb type    | TL-D                            |
| Average Lifetime (h)     | 0                               |
| Maximum Wattage Rating   | 36                              |
| Suitable for bulb type   | TL-D                            |
| Dimmable                 | Not Dimmable                    |
| Fixture Connection       | Wago 251                        |
| Amount of bulbs required | 1                               |
| Product Type Category    | Accessory - Fluorescent Ballast |

## Lamp Information

|        |              |
|--------|--------------|
| EOC8   | 91164000     |
| Series | HF-Performer |

## Sensor Information

|                |           |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

